



⊞ Features	
■ Built-in Web Server	
■ Support Modbus TCP/UDP Protocols	
■ Powerful 32-bit MCU Handles Efficient Network Traffic	
■ 2-port Ethernet Switch (LAN Bypass) for Daisy-Chain Wiring	
■ Dual Watchdog	
I/O Pair Connection (Push and Polling)	
Easy Firmware Update via Ethernet	
LED Display to Indicate the I/O status	
■ Wide Operating Temperature Range: -25 ~ +75°C	
■ Built-in I/O	
□ DI/Counter: 6 Channels	
□ Power Relay: 6 Channels	
CE FE ROHS	

Introduction

The ET-2260 provides 6 wet contact Digital Input channels and 6 Form A electromechanical Relays. With 2 Ethernet ports, the ET-2260 allows daisy chain connection which permits the flexibility in locating devices, eases installation and lowers infrastructure costs. It features 8 kV ESD protection, 4 kV EFT protection, 3 kV surge and 3750 VDC I/O isolation to enhance noise protection capabilities in industrial environments. Each input channel can be used as a 32-bit counter. The power-on value and safe value of relay are configurable.


■ System Specifications -

System			
CPU	32-bit ARM		
Communication			
Ethernet Port	2 x RJ-45, 10/100 Base-TX, Switch Ports		
Protocol	Modbus TCP, Modbus UDP		
Security	Password and IP Filter		
I/O Pair Connection	Yes (Push, Polling)		
Dual Watchdog	Yes, Module, Communication (Configurable)		
LAN Bypass	Yes		
LED Indicators			
System Running	Yes		
Ethernet Link/Act	Yes		
DI/DO status	Yes		
2-Way Isolation			
Ethernet	1500 VDC		
I/O	3750 VDC		
EMS Protection			
ESD (IEC 61000-4-2)	±8 kV Contact for Each Terminal and ±16 kV Air for Random Point		
EFT (IEC 61000-4-4)	±4 kV for Power Line		
Surge (IEC 61000-4-5)	±3 kV for Power Line		
Power			
Reverse Polarity Protection	Yes		
Powered from Terminal Block	+10 ~ +30 VDC		
Consumption	3.3 W (Max.)		
Mechanical			
Dimensions (L x W x H)	127 mm x 33 mm x 99 mm		
Installation	DIN-Rail Mounting		
Environment			
Operating Temperature	-25 ~ +75°℃		
Storage Temperature	-30 ~ +80°C		
Humidity	10 ∼ 90% RH, Non-condensing		

■ I/O Specifications _____

Digital Input/Counter			
Channels		6	
Contact		Wet Contact	
Sink/Source	ce (NPN/PNP)	Sink/Source	
On Voltage Level		+5 V _{DC} ~ +50 V _{DC}	
Off Voltage Level		+1 V _{DC} Max.	
Input Impedance		7.5 kΩ	
	Max. Count	4,294,967,295 (32 bits)	
Counters	Max. Input Frequency	3 kHz	
	Programmable Digital Filter	1 ~ 6500 ms (0.08 Hz ~ 500 Hz)	
Overvoltag	ge Protection	+70 VDC	
Power Re	Power Relay		
Channels		6	
Туре		Power Relay, Form A (SPST N.O.)	
Contact Rating		5 A @ 250 VAC/24 VDC (Resistive Load)	
Min. Contact Load		10 mA @ 5 V	
Operate Time		10 ms (max.)	
Release Time		5 ms (max.)	
Mechanical Endurance		2×10^7 ops.	
Electrical Endurance		10 ⁵ ops.	
Power-on Value		Yes, Configurable	
Safe Value		Yes, Configurable	

■ Pin Assignments —



Terminal No.	Assignment		
PWR	F.G. GND + Vs		
ETH1			
ETH2			
Terminal No.	Pin Assignment	Pin Assignment	Termi No
01	NO0	GND	02
03	COM0	DI0	04
05	NO1	DI1	06
07	COM1	DI2	08
09	NO2	DI3	10
11	COM2	DI4	12

DI5

NO5

COM5

сомз

NO4

COM4

DICOM

14

16

18

2

20

Wire Connections -

Digital Input/ Counter	Readback as 1	Readback as 0	
Dry Contact	Close to GND	Open	
	DIX	DI.GND +S5 V DIx	
Sink	+10 ~ +50 VDC	OPEN or <4 VDC	
	DIX 10K	DIX 10K	
	+10 ~ +50 VDC	OPEN or <4 VDC	
Source	DIX 10K	DIX 10K	

ON State Power Relay Load NOx (AC/DC) COMx **OFF State** Relay Output Readback as 0 Load NOx (AC/DC) COMx

Note: When inductive loads are connected to the relays, a large counter electromotive force may occur when the relay actuates because of the energy stored in the load. These flyback voltages can severely damage the relay contacts and greatly shorten the relay life. Limit these flyback voltages at your inductive load by installing a flyback diode for DC loads or a metal oxide varistor for AC loads.

■ Ordering Information —

Ethernet I/O Module with 2-port Ethernet Switch, 6-ch ET-2260 CR Relay Output and 6-ch DI (RoHS)

Related Products ___

NS-205 CR	Unmanaged 5-Port Industrial Ethernet Switch with Power Input $+10 \sim +30 \; \text{VDC}$ (RoHS)
NS-208 CR	Unmanaged 8-port Industrial 10/100 Base-TX Ethernet Switch with Power Input +10 \sim +30 Vpc (RoHS)
DIN-KA52F CR	24 V/1.04 A, 25 W Power Supply with DIN-Rail Mounting (RoHS)
GPSU06U-6	24 V/0.25 A (max.) Power Supply

