Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	1/10

# How to use ActiveSync through the Serial port?

Platform	OS version	WinPAC/ViewPAC utility version
WP-8x3x	1.1.3.0 and later	All versions
WP-8x4x	1.4.2.1 and later	All versions
VP-25W1	1.1.0.0 and later	All versions
VP-23W1	1.1.1.1 and later	All versions
VP-4131	All versions	All versions
WP-5000	All versions	All versions

## **Tips & Warnings**




The WP-8141 and WP-8131 platforms don't support ActiveSync.

ActiveSync helps you to synchronize the files on your host PC with the WinPAC/ViewPAC.

To use ActiveSync, perform the following steps:

**Step1: Set** ActiveSync on WinPAC/ViewPAC.

1.1. Click Start-->Settings-->Network and Dial-up Connections.




Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	2/10

1.2. Double Click the "Make New Connection" icon.



1.3. Select the "Direct Connection" radio button and then click the "Next" button.



Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	3/10


1.4. Choose ICPDAS-COM4 from the "Select a device" comboBox and Click the "Configure" button.


### **Tips & Warnings**



WP-8000 COM4 is only used to allow the ActiveSync to communicate with the PC via the RS-232 serial, and VP-25W1/VP-23W1 **COM3** is only used to allow the ActiveSync to communicate with the PC. If you choose other COM Ports, ActiveSync will not function.

WP-8x4x/WP-8x3x







Classification	System and Ap	System and Application FAQ on WinCE PAC					2-002-02
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	4/10

1.5. Select the appropriate Baud Rate and Click the "OK" button.

#### **Tips & Warnings**




The Baud Rate range for different ActiveSync versions is:

For ActiveSync version 3.7 or 3.7.1, 19200bps or 57600bps can be selected.

For ActiveSync version 3.8 or 4.5, 19200bps, 38400bps, 57600bps or 115200bps can be selected.

The ActiveSync program from the PC side does not need to set Baud Rate.



Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	5/10


1.6. Click Start-->Settings-->Control Panel.



1.7. Click the "PC connection" icon.



1.8. Check the "Enable direct connections to the desktop computer" checkbox and Click the "Change Connection" button.



Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	6/10

1.9. Change to a new connection by selecting "My Connection" from the conboBox, and then click the "OK" button.




1.10. Click the "OK" button.




Step2: Set ActiveSync on the PC side.

- 2.1. Install Microsoft Windows Mobile Device Center 6.1 software on PC
- 2.2. Run Windows Mobile Device Center




Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	7/10

### 2.3. Check "Connections settings".



2.4. Click the COM1 of the comboBox and click the "OK" button. (The WP5000 need check the "Allow USB connections".)




2.5. Click the "continue" button

Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	8/10

## **Example: Synchronize** a file between the PC and WinPAC/ViewPAC.

1. Click the "Connect without setting up your device" button.




2. Click the "Browse the contents of your device" menu option.



Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	9/10

3. Copy the file to the target folder on the devices.



Classification	System and Ap	System and Application FAQ on WinCE PAC					
Author	Tunglu-Yu	Version	1.0.1	Date	2013/08/16	Page	10/10

# **Revision History**

Revision	Date	Description
1.0.1	2013/08/06	NEW: Added support information for WP-5000 and VP-4131.
1.0.0	2010/02/12	Initial release